

ABOUT SRNE

- $\hfill \square$ SRNE 15 years in PV industry, committed to independent R&D and production.
- ☐ Holds over 200 patents in energy storage, with unique industry—leading technologies.
- ☐ Chooses top-quality international components to deliver high-value products to customers.
- $\hfill \Box$ Upholds values of customer priority, proactivity, responsibility, and innovative breakthroughs.



MODEL		HFP4850S80-H		
INVERTER OUTPUT				
Rated Output Power		5,000W		
Max.Peak Power		10000VA		
Rated Output Voltage		230Vac±5% (Single-Phase/Three-Phase(Parallel))		
Load Motor Capacity		4HP		
Rated Frequency		50/60Hz ±0.3		
Waveform		Pure sine wave		
Switch Time		10ms (typical)		
BATTERY				
Battery Type		Lead-Acid / Li-ion / User-Define		
Rated Battery Voltage		48V		
Battery Volatge Range		40.0Vdc~60Vdc ± 0.6Vdc		
Max. Solar Charging Current		80A		
Max. Grid/Generator Charging Current		60A		
Max. Hybrid Charging Current		80A		
SOLAR INPUT				
No. Of MPPT		1		
Max.PV Array Power		5,500W		
Max. Input Current		22A		
Max. Open Circuit Voltage		500Vdc		
MPPT Voltage Range		120~450Vdc		
GRID/GENERATOR INPUT				
Input Voltage Range		UPS mode: 170~280Vac; APL mode: 90~280Vac		
Input Frequency Range		50/60Hz		
Bypass Overload Current		40A		
EFFICIENCY				
MPPT Tracking Efficiency		99.9%		
Max. Efficiency		97.5%		
GENERAL DATA				
Dimension	426m	m*322mm*124mm	Parallel Capacity	1∼6 Units
Weight		10.5 kg	Cooling Method	Fan Cooling
Protection Degree	IP	20 Only Indoor	Warranty	2 years
Humidity range	0~100%		Communication	RS485/CAN/USB/Dry Contact
External Module (Optional)	Wi-Fi/GPRS		Temperature	−10°C~55°C
Certificate	CE(IEC62109-1)/CETL(UL1741C22.2NO.107.1)/FCC/SAA			

PROTECTION

Battery Discharge Average Current Overcurrent Software Protection, Battery Overcurrent Hardware Protection, Charging Overvoltage Protection, Internal Battery Boost Circuit Overvoltage Protection, Internal Battery Boost Circuit Overvoltage Software Protection, Solar Input Voltage Overvoltage Protection, Solar Charging Overcurrent Software Protection, Solar Charging Overcurrent Hardware Protection, Bypass AC Output Overload Protection, Inverter AC Output Overload Protection, Inverter AC Output Overcurrent Hardware protection, inverter AC output short circuit protection, solar charging radiator over-temperature protection, inverter AC output with load or AC charging radiator over-temperature protection